

BTD-E886

Технические характеристики

По вопросам продаж и поддержки обращайтесь:

Алматы (7273)495-231	Казань (843)206-01-48	Новокузнецк (3843)20-46-81	Смоленск (4812)29-41-54
Архангельск (8182)63-90-72	Калининград (4012)72-03-81	Новосибирск (383)227-86-73	Сочи (862)225-72-31
Астрахань (8512)99-46-04	Калуга (4842)92-23-67	Омск (3812)21-46-40	Ставрополь (8652)20-65-13
Барнаул (3852)73-04-60	Кемерово (3842)65-04-62	Орел (4862)44-53-42	Сургут (3462)77-98-35
Белгород (4722)40-23-64	Киров (8332)68-02-04	Оренбург (3532)37-68-04	Тверь (4822)63-31-35
Брянск (4832)59-03-52	Краснодар (861)203-40-90	Пенза (8412)22-31-16	Томск (3822)98-41-53
Владивосток (423)249-28-31	Красноярск (391)204-63-61	Пермь (342)205-81-47	Тула (4872)74-02-29
Волгоград (844)278-03-48	Курск (4712)77-13-04	Ростов-на-Дону (863)308-18-15	Тюмень (3452)66-21-18
Вологда (8172)26-41-59	Липецк (4742)52-20-81	Рязань (4912)46-61-64	Ульяновск (8422)24-23-59
Воронеж (473)204-51-73	Магнитогорск (3519)55-03-13	Самара (846)206-03-16	Уфа (347)229-48-12
Екатеринбург (343)384-55-89	Москва (495)268-04-70	Санкт-Петербург (812)309-46-40	Хабаровск (4212)92-98-04
Иваново (4932)77-34-06	Мурманск (8152)59-64-93	Саратов (845)249-38-78	Челябинск (351)202-03-61
Ижевск (3412)26-03-58	Набережные Челны (8552)20-53-41	Севастополь (8692)22-31-93	Череповец (8202)49-02-64
Иркутск (395)279-98-46	Нижний Новгород (831)429-08-12	Симферополь (3652)67-13-56	Ярославль (4852)69-52-93
Россия (495)268-04-70	Киргизия (996)312-96-26-47	Казахстан (7172)727-132	



BTD-E886(LD)

Optoelectronics Device Burn-in System/Dedicated Burn-in System for LD/BTD-E886

The system is designed to perform high temp. constant current life test & power burn-in screening for laser diode in various TO packages.
and high temp.power burn-in screening for optocoupler is also supported.

Test Standard



Max Test Temp.

Chamber&BIB: 150°C;Horizontal air circulating design



Zone Configuration

10 zones,each with independent power supply,which can burn-in 10 kinds of DUTs in different voltage.



E-load*64

With 64 constant current E-load of 0~200mA per slot, greatly improve burn-in ability.



Interface Definition

4 gold fingers are reserved for each DUT, and its electrical performance definition can be converted by configuring different adapter boards on the drive board

Chamber

Brand	GWS PH-401
Dimension	600*600*1200(mm)
Air circulating	Horizontal air circulating design
Temperature	Ambient ~ 150°C
Temp. uniformity	125°C±3°C(null load); Fluctuation:±0.5°C

Capacity

Zone QTY.	10
Slot	40
DUT per slot/ Total	64/2560

Power Supply

QTY.	10 sets
-------------	---------

Output 12V/100A 、 20V/1200A and more spec.

Driver Board

QTY. 40 pcs

Constant current source 64 channels of constant current source (0~200.0mA)

PD Im detection Range : 10 μ A ~ 2000 μ A ; Accuracy : \pm (2%+1 μ A)

LD detection Range : 10 μ A ~ 2000 μ A ; Accuracy : \pm (2%+1 μ A)

Voltage detection range Range(PD、 LD) : 0.00V ~ 9.99V ; Accuracy : \pm (2%+0.01V)

Burn-in Board

Substrate material High Tg substrate

Temp. up to 150 $^{\circ}$ C / 175 $^{\circ}$ C

Dimension 290*300(mm)

Equipment

Dimension 1900W*1300D*2000H(mm)

Electrical requirement A.C.220V \pm 10% / 50Hz

Power/Weight 10KW / 800KG

По вопросам продаж и поддержки обращайтесь:

Алматы (7273)495-231
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Россия (495)268-04-70

Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Киргизия (996)312-96-26-47

Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Казахстан (7172)727-132

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93