

BTSR-E160

Технические характеристики

По вопросам продаж и поддержки обращайтесь:

Алматы (7273)495-231	Казань (843)206-01-48	Новокузнецк (3843)20-46-81	Смоленск (4812)29-41-54
Архангельск (8182)63-90-72	Калининград (4012)72-03-81	Новосибирск (383)227-86-73	Сочи (862)225-72-31
Астрахань (8512)99-46-04	Калуга (4842)92-23-67	Омск (3812)21-46-40	Ставрополь (8652)20-65-13
Барнаул (3852)73-04-60	Кемерово (3842)65-04-62	Орел (4862)44-53-42	Сургут (3462)77-98-35
Белгород (4722)40-23-64	Киров (8332)68-02-04	Оренбург (3532)37-68-04	Тверь (4822)63-31-35
Брянск (4832)59-03-52	Краснодар (861)203-40-90	Пенза (8412)22-31-16	Томск (3822)98-41-53
Владивосток (423)249-28-31	Красноярск (391)204-63-61	Пермь (342)205-81-47	Тула (4872)74-02-29
Волгоград (844)278-03-48	Курск (4712)77-13-04	Ростов-на-Дону (863)308-18-15	Тюмень (3452)66-21-18
Вологда (8172)26-41-59	Липецк (4742)52-20-81	Рязань (4912)46-61-64	Ульяновск (8422)24-23-59
Воронеж (473)204-51-73	Магнитогорск (3519)55-03-13	Самара (846)206-03-16	Уфа (347)229-48-12
Екатеринбург (343)384-55-89	Москва (495)268-04-70	Санкт-Петербург (812)309-46-40	Хабаровск (4212)92-98-04
Иваново (4932)77-34-06	Мурманск (8152)59-64-93	Саратов (845)249-38-78	Челябинск (351)202-03-61
Ижевск (3412)26-03-58	Набережные Челны (8552)20-53-41	Севастополь (8692)22-31-93	Череповец (8202)49-02-64
Иркутск (395)279-98-46	Нижний Новгород (831)429-08-12	Симферополь (3652)67-13-56	Ярославль (4852)69-52-93
Россия (495)268-04-70	Киргизия (996)312-96-26-47	Казахстан (7172)727-132	



BTSR-E160(Solid state relay)

Solid State Relay High Temp. Burn-in System

The system is designed to perform low-level life test and burn-in screening under ambient&high temp. condition for various packages'electromagnetic relay including Single coil monostable, single coil magnetic holding, double coil magnetic holding relay

Chamber

Brand	GWS/ ESPEC PH-201
Dimension	600*600*600(mm)
Air circulating	Horizontal air circulating design
Temperature	150°C
Temp. uniformity	150°C±3°C(null load); Fluctuation:±0.5°C

Capacity

Zone QTY.	8
Slot	16
DUT per slot/ Total	16 / 256

Coil excitation(Bulk PS)

QTY.	16 sets
Output	0 ~ 80V/30A(8 sets), 0 ~ 32V/2A(8 sets)

Coil excitation(DC/DC Converter)

Configuration	16 channels of DC/DC Converter per zone as input power
Input	Voltage range:3~30.00V; Current up to 50.0mA
Output	Voltage range(contact drop):0.02~10.00V; Current up to 10.0A

Programmable coil excitation pulse

接通时间	0.05S ~ 999h (adjustable)
关断时间	0.05S ~ 999h (adjustable)

Burn-in mode

Coil excitation	Parallel connect 16 DUTs' input pins and detect each DUT's input voltage at. Burn-in mode includes current mode and voltage mode.
------------------------	-----------------------------------------------------------------------------------------------------------------------------------

Output	Series connect 16 DUTs' output pins and detect each DUT's contact voltage drop
---------------	--------------------------------------------------------------------------------

E-load

Configuration	1 set of E-load per slot; Current:0~10A
----------------------	-----------------------------------------

Burn-in Board

Substrate material	High Tg substrate
---------------------------	-------------------

Temp. up to	150°C / 175°C / 200°C
--------------------	-----------------------

Dimension	290*600(mm)
------------------	-------------

Equipment

Dimension	1430W*1400D*2000H(mm)
------------------	-----------------------

Electrical requirement	A.C.220V±10% / 50Hz
-------------------------------	---------------------

Power/Weight	8KW / 600KG
---------------------	-------------

По вопросам продаж и поддержки обращайтесь:

Алматы (7273)495-231
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Россия (495)268-04-70

Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Киргизия (996)312-96-26-47

Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Казахстан (7172)727-132

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93