

BTW-E361

По вопросам продаж и поддержки обращайтесь:

Алматы (7273)495-231	Казань (843)206-01-48	Новокузнецк (3843)20-46-81	Смоленск (4812)29-41-54
Архангельск (8182)63-90-72	Калининград (4012)72-03-81	Новосибирск (383)227-86-73	Сочи (862)225-72-31
Астрахань (8512)99-46-04	Калуга (4842)92-23-67	Омск (3812)21-46-40	Ставрополь (8652)20-65-13
Барнаул (3852)73-04-60	Кемерово (3842)65-04-62	Орел (4862)44-53-42	Сургут (3462)77-98-35
Белгород (4722)40-23-64	Киров (8332)68-02-04	Оренбург (3532)37-68-04	Тверь (4822)63-31-35
Брянск (4832)59-03-52	Краснодар (861)203-40-90	Пенза (8412)22-31-16	Томск (3822)98-41-53
Владивосток (423)249-28-31	Красноярск (391)204-63-61	Пермь (342)205-81-47	Тула (4872)74-02-29
Волгоград (844)278-03-48	Курск (4712)77-13-04	Ростов-на-Дону (863)308-18-15	Тюмень (3452)66-21-18
Вологда (8172)26-41-59	Липецк (4742)52-20-81	Рязань (4912)46-61-64	Ульяновск (8422)24-23-59
Воронеж (473)204-51-73	Магнитогорск (3519)55-03-13	Самара (846)206-03-16	Уфа (347)229-48-12
Екатеринбург (343)384-55-89	Москва (495)268-04-70	Санкт-Петербург (812)309-46-40	Хабаровск (4212)92-98-04
Иваново (4932)77-34-06	Мурманск (8152)59-64-93	Саратов (845)249-38-78	Челябинск (351)202-03-61
Ижевск (3412)26-03-58	Набережные Челны (8552)20-53-41	Севастополь (8692)22-31-93	Череповец (8202)49-02-64
Иркутск (395)279-98-46	Нижний Новгород (831)429-08-12	Симферополь (3652)67-13-56	Ярославль (4852)69-52-93
Россия (495)268-04-70	Киргизия (996)312-96-26-47	Казахстан (7172)727-132	



BTW-E361 (Co emitter / Water-cooled)

High Power Transistor Burn-in System--Co.-emitter / Water cooled

The system can perform CFOL test and power burn-in screening with Tc controlled for MOS&Darlington transistor with rating power 20W~300W, and part of transistors. Applicable to F0, F1, F2 (fine), F2-3 (coarse), To-3P and other packages.

Max Test Temperature

Chamber&BIB: 150°C/175°C/200°C are optional

Zone configuration

4~8 zones, each with independent power supply, which can burn-in 4~8 kinds of DUTs in different voltage requirements (up to 10kV) at the same time

Auto-loading Burn-in Parm.

Auto-apply Temp. Voltage and other parm. to the DUT according to the software setting

Real time monitoring

Real-time monitoring of all DUTs' data & over limit status.

Water-cooled system

Control	Micro PC control; Water temp. setting range: 12°C~35°C
Coolant	DI water(or purified water); Auto-water replenishment;
Protection	Compressor protection; Motor overload protection; Low water temp.protection;Water-break protection;Phase failure&phase sequence protection
Cooling capacity	8KW
Water circulation	25L/min
Capacity	
Slots	8
DUT QTY. per slot/ Total	6/48
Power Supply	
PSU QTY.	8 sets+ s sets of Auxiliary heating PSU
Output	30V~80A/Auxiliary heating PSU:80V~30A
Driver Board	
QTY.	8pcs
Constant current	48 channels; output:0.01A~10.00A

Voltage detection	Range : 0.00V ~ 99.9V ; Accuracy : $\pm(1\%+0.1V)$
Voltage detection accuracy	$\pm(1\%+3LSB)$
Tc	50 ~ 100°C ; Accuracy : $\pm(2\%+1^\circ C)$; fluctuation : $\pm 3^\circ C$
Fixture	
Structure	Universal fixture with clamshell&vertical screw in design
DUT position dimension	60mm*100mm
Equipment	
Electrical requirement	A.C.380V $\pm 10\%$ / 50Hz
Power/Weight	16KW / 600KG

По вопросам продаж и поддержки обращайтесь:

Алматы (7273)495-231
Архангельск (8182)63-90-72
Астрахань (8512)99-46-04
Барнаул (3852)73-04-60
Белгород (4722)40-23-64
Брянск (4832)59-03-52
Владивосток (423)249-28-31
Волгоград (844)278-03-48
Вологда (8172)26-41-59
Воронеж (473)204-51-73
Екатеринбург (343)384-55-89
Иваново (4932)77-34-06
Ижевск (3412)26-03-58
Иркутск (395)279-98-46
Россия (495)268-04-70

Казань (843)206-01-48
Калининград (4012)72-03-81
Калуга (4842)92-23-67
Кемерово (3842)65-04-62
Киров (8332)68-02-04
Краснодар (861)203-40-90
Красноярск (391)204-63-61
Курск (4712)77-13-04
Липецк (4742)52-20-81
Магнитогорск (3519)55-03-13
Москва (495)268-04-70
Мурманск (8152)59-64-93
Набережные Челны (8552)20-53-41
Нижний Новгород (831)429-08-12
Киргизия (996)312-96-26-47

Новокузнецк (3843)20-46-81
Новосибирск (383)227-86-73
Омск (3812)21-46-40
Орел (4862)44-53-42
Оренбург (3532)37-68-04
Пенза (8412)22-31-16
Пермь (342)205-81-47
Ростов-на-Дону (863)308-18-15
Рязань (4912)46-61-64
Самара (846)206-03-16
Санкт-Петербург (812)309-46-40
Саратов (845)249-38-78
Севастополь (8692)22-31-93
Симферополь (3652)67-13-56
Казахстан (7172)727-132

Смоленск (4812)29-41-54
Сочи (862)225-72-31
Ставрополь (8652)20-65-13
Сургут (3462)77-98-35
Тверь (4822)63-31-35
Томск (3822)98-41-53
Тула (4872)74-02-29
Тюмень (3452)66-21-18
Ульяновск (8422)24-23-59
Уфа (347)229-48-12
Хабаровск (4212)92-98-04
Челябинск (351)202-03-61
Череповец (8202)49-02-64
Ярославль (4852)69-52-93